

# Crazy8 2.0

## What's new

### ● Polyphonic CV

Set a chord to track 5 (CV1) and tracks 6 (CV2), 7 (CV3) and 8 (CV4) will play 3 notes of the chord

### ● Custom CV calibration

Hold the encoder pressed at startup to enter CV calibration mode.

- Select a target note:

Now hold shift and turn the encoder to select one of the 64 target notes (all CV outputs will send the CV your are tuning)

- Tuning the target note

Now release shift and simply turn the encoder to fine tune the pitch. Hold tempo for larger increments.

- Resetting to factory 1V/oct setting

Press the encoder down at any time to return to the factory CV value (target note only)

- Saving/Exiting calibration mode

Press run to save the settings, all tunings will be saved to memory. Then power cycle crazy8 when all the LEDs go blank.

### ● Pattern change at end of cycle

Now crazy8 will change pattern at the end of it's current pattern cycle, this helps keep things in sync and enables jumping between 2 patterns without cycling through each one.

### ● Monitor mode

Enable or disable monitor mode by holding rest + run (stored between power cycles).

Now can be used as a MIDI/CV keyboard!

### ● Rec on/off

Hold shift and press run to enable/disable MIDI recording.

If rec is active, the run LED will flash and you can punch notes into in pattern of the selected track via MIDI when in step mode.

### ● Shift shows all!

When in step mode, hold shift to display the active steps of your pattern. Step with chords will flash